


Powershred® 8C/8Cd The World's Toughest Shredders®





KEY

- A. CD entry (8Cd only)
- B. Paper/card entry
- C. Shredder head
- D. See safety instructions below
- E. Bin
- F. Window
- G. Safety lock



H. Control switch and LEDs

I Reverse

O 2.0ff

⇒ 3. Auto-On (green)

4. Overheat (red)

CAPABILITIES

Will shred:

8C: Paper, plastic credit cards, staples and small paper clips 8Cd: Paper, plastic credit cards, staples, small paper clips and CD/DVDs

Will not shred: Unopened junk mail, continuous forms, adhesive labels, transparencies, newspaper, CD/DVDs (8C only), cardboard, large paper clips, laminates, file folders, X-rays or plastic other than noted above

Paper shred size:

Maximum:

 Sheets per pass
 8*

 Cards per pass
 1*


 CDs per pass (8Cd only)
 1*

 Paper width
 220mm

*70g A4 paper at 220-240v, 50/60Hz, 1.0Amps; heavier paper, humidity or other than rated voltage may reduce capacity. Maximum recommended daily usage rates: 50 sheets; 5 cards.


▲ WARNING: IMPORTANT SAFETY INSTRUCTIONS — Read Before Using!

























 Do not use if damaged or defective. Do not disassemble shredder. Do not place near or over heat source or water.

- Avoid touching exposed cutting blades under shredder head.
- Shredder must be plugged into a wall outlet or socket of the voltage and amperage designated on the label. The outlet or socket must be installed near the equipment and easily accessible. Energy converters, transformers, or extension cords should not be used with this product.
- FIRE HAZARD Do NOT shred greeting cards with sound chips or batteries.
- For indoor use only.
- Unplug shredder before cleaning or servicing.


BASIC SHREDDING OPERATION



Continuous operation: Up to 3-minute maximum

NOTE: Shredder runs briefly after each pass to clear entry. Continuous operation beyond 3-minutes will trigger 30-minute cool down period.

PAPER/CARD OR CD (8Cd only)




Plug in and set to Auto-On (▷)



Feed paper/card straight into paper entry and release



Hold CD at edge, feed into center of entry and release (8Cd only)



When finished shredding, set to Off (O)



Safety Lock prevents accidental operation. $\theta_{\hat{a}}$ To set, wait for shredding to stop, set control switch to Off (0) position, then slide black button down. $\theta_{\hat{a}}$ To unlock, slide black button up. For greater safety, always unplug shredder after use.

PRODUCT MAINTENANCE

OILING SHREDDER (4)




All cross-cut shredders require oil for peak performance. If not oiled, a machine may experience diminished sheet capacity, intrusive noise when shredding and could ultimately stop running. To avoid these problems, we recommend you oil your shredder each time you empty your waste bin.

FOLLOW OILING PROCEDURE BELOW AND REPEAT TWICE



Set to Off (O)





*Apply oil across entry Set to Reverse (ICIC) for 2-3 seconds

*Only use a non-aerosol vegetable oil in long nozzle container such as Fellowes 35250



TROUBLESHOOTING

PAPER JAM



Set to Reverse (⋈) for 2-3 seconds



Alternate slowly back and forth



Set to Off (O) and unplug



Gently pull uncut paper from paper entry. Plug in



Set to Auto-On (▷) and resume shredding

Shredder doesn't start:

Make sure switch is in auto position (\triangleright).

Make sure safety lock is in unlock position.

Make sure head is on basket correctly. Check for jam.

Remove and empty basket.

Wait 30 minutes for motor to cool down.

LIMITED PRODUCT WARRANTY

Limited Warranty: Fellowes, Inc. ("Fellowes") warrants the parts of the machine to be free of defects in material and workmanship and provides service and support for 2 years from the date of purchase by the original consumer. Fellowes warrants the cutting blades of the machine to be free from defects in material and workmanship for 3 years from the date of purchase by the original consumer. If any part is found to be defective during the warranty period, your sole and exclusive remedy will be repair or replacement, at Fellowes' option and expense, of the defective part. This warranty does not apply in cases of abuse, mishandling, failure to comply with product usage standards, shredder operation using an improper power supply (other than listed on the label), or unauthorized repair. Fellowes reserves the right to charge the consumers for any additional costs

incurred by Fellowes to provide parts or services outside of the country where the shredder is initially sold by an authorized reseller. ANY IMPLIED WARRANTY, INCLUDING THAT OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE. IS HEREBY LIMITED IN DURATION TO THE APPROPRIATE WARRANTY PERIOD SET FORTH ABOVE. In no event shall Fellowes be liable for any consequential or incidental damages attributable to this product. This warranty gives you specific legal rights. The duration, terms, and conditions of this warranty are valid worldwide, except where different limitations, restrictions, or conditions may be required by local law. For more details or to obtain service under this warranty, please contact us or your dealer.

Our goods come with guarantees that cannot be excluded under the Australian Consumer Law. You are entitled to a replacement or refund for a major failure and for compensation for any other reasonably foreseeable loss or damage. You are also entitled to have the goods repaired or replaced if the goods fail to be of acceptable quality and the failure does not amount to a major failure. The benefits under Fellowes' Warranty are in addition to other rights and remedies under a law in relation to the shredder.



CUSTOMER SERVICE & SUPPORT

www.fellowes.com

Australia: 1 800 33 11 77 Europe: 00-800-1810-1810

United Kingdom: +44 (0) 1302 836836

United States: 001-800-514-9057

Declaration of Conformity

Fellowes, Inc.

Unit 2 Ontario Drive, New Rossington, Doncaster, DN11 OBF, England declares that the product models 8C and 8Cd conform with the requirements of the Restriction of Hazardous Substances Directive (2011/65/EU), the Low Voltage Directive (2014/35/EU), the Electromagnetic Compatibility Directive (2014/30/EU), the WEEE directive (2012/19/EU), and below harmonized European EN Standards.

Safety: EN60950-1: 2006/A2:2013

EMC Standard: EN55014-1:2006+A1:2009+A2:2011

EN55014-2:1997+A1:2001+ A2:2008

EN61000-3-2:2014 EN61000-3-3:2013

Year Affixed: 17

Itasca, Illinois, USA January 1, 2018 John Fellowes

W.E.E.E.

This product is classified as Electrical and Electronic Equipment. Should the time come for you to dispose of this product please ensure that you do so in accordance with the European Waste of Electrical and Electronic Equipment (WEEE) Directive and in compliance with local laws relating to this directive.

For more information on the WEEE Directive please visit www.fellowes.com/WEEE

